


Orientation magnet



Product	
HOM	Orientation magnet
HOMZ	Special Orientation magnet

Coil type	
A	Aluminum band coils
C	Copper wire coils

Power consumption	
xxkx	Examples: 00k5 = 0,5kW / 11k0 = 11,0kW

Voltage	
xxx	Examples: 024 = 24V DC / 150 = 150V DC

Pole opening [mm]	

Pole dimensions [mm]	
...x....	Pole width x pole height [mm] (if rectangular)
D...	Diameter [mm] (if round)

Yoke execution	
L	Laminated transformer steel core
S	Solid iron core

Cooling options	
B	Basic (no forced cooling)
F	Forced fan cooling
Z	Special